



# Balance 580X

A Proven Solution for Reliable Internet



**TAA** COMPLIANT



## Configurable Multi-Gig Ports

Configure the 2.5G PoE++ ports as WAN or LAN to match your network topology. Adapt to changing deployment needs while maximizing flexibility and infrastructure efficiency.

# 1 Gb

Up to 500 SpeedFusion Peers

## Gigabit SPEEDFUSION Throughput

Deliver gigabit bonding to meet enterprise-grade network demands. Maintain consistent performance across multiple remote sites, ensuring bandwidth and reliability at scale.



## One PoE++ Platform, Clean Deployments

Easily integrate 5G with Peplink Dome or Antenna MAX solutions while powering heavy-duty devices such as pan-tilt-zoom cameras and Wi-Fi 7 access points. Streamline deployment by eliminating extra injectors and cabling.

### PoE++ Output x8






## Flexible, Centralized SIM Management

Seamlessly manage SIMs for connected Dome or Antenna MAX with a **SIM Injector FlexModule\***. Maintain optimal 5G performance with increased carrier redundancy and easier SIM provisioning.



FlexModule Mini **SIM Injector**

\* Compatible with FlexModule Mini (LTE/5G/SIM Injector). FlexModule units are sold separately.





# InControl<sup>2</sup>

## Centralized Network Management




Manage access points and switches alongside all other Peplink devices via **InControl<sup>2</sup>**, all from a single pane of glass.



Maintain local control from the router interface when needed for on-site management.

# Balance 580X



## Specifications

<b>WAN Interface</b>	4x 2.5G Multi-Gig Ethernet <sup>1 2</sup> 1x 10G Multi-Gig Ethernet <sup>1</sup> 2x USB-C Interface <sup>3</sup> 1x Optional Cellular <sup>4</sup>	<b>Remote User Access</b>	Yes
<b>LAN Interface</b>	4x 2.5G Multi-Gig Ethernet <sup>1 2</sup> 1x 10G Multi-Gig Ethernet <sup>1</sup>	<b>LACP (802.3ad) NIC Bonding</b>	Yes <sup>6</sup>
<b>Router Throughput</b>	8Gbps	<b>1U Rack-mount</b>	Yes
<b>SpeedFusion VPN Throughput</b>		<b>Power Input</b>	AC Input 100V - 240V
- No Encryption	1Gbps	<b>Power Output</b>	8x 802.3bt Type 4 PoE++
- 256-bit AES	1Gbps	<b>Power Consumption</b>	37W (nominal) / 39W (max. without PoE and USB-C Output)
<b>Recommended Users</b>	500-2000	<b>Total PoE Power Budget</b>	720W
<b>SpeedFusion VPN Peers</b>	100 / 300 <sup>5</sup> / 500 <sup>5</sup>	<b>Dimensions</b>	17.3 x 12.2 x 1.73 inches / 440 x 310 x 44 mm
<b>Maximum Number of Controlled AP / Switch</b>	100	<b>Weight</b>	9.39 pounds / 4.26 kg
<b>SpeedFusion Features</b>	Hot Failover, Smoothing, Bandwidth Bonding	<b>Operating Temperature</b>	32°– 104° F / 0°– 40° C
<b>Central Management</b>	InControl 2	<b>Humidity</b>	10% to 95% (non-condensing)
<b>Drop-In Mode</b>	Yes	<b>Certifications</b>	FCC, CE, RoHS
<b>High Availability</b>	Yes	<b>Package Content</b>	1x Balance 580X 1x Power Cord (ACW-614) 4x Rubber Feet 1x Ear Rack Mount Kit with screws
<b>Content Filtering</b>	Full	<b>SIM Options</b>	Mini-SIM (2FF) <sup>4</sup> Peplink eSIM <sup>4</sup> BYO eSIM (2 profiles) <sup>4</sup> RemoteSIM from SIM Injector <sup>4</sup> FusionSIM <sup>4</sup>
<b>AP &amp; Switch Controller</b>	Standard	<b>Warranty</b>	1-Year Limited Warranty
<b>Edge Computing</b>	Docker (8GB Internal Storage / External Storage via USB Port)		

<sup>1</sup> 10G is backward compatible with FE / GE / 2.5G / 5G; 2.5G is backward compatible with GE and FE.

<sup>2</sup> Ethernet WAN ports 2-5 are configurable WAN/LAN ports. WAN/LAN Configuration is changeable on the Web Admin.

<sup>3</sup> USB-C port can deliver 5V at 3A to power the Peplink Adapters or other USB dongles for USB WAN.

<sup>4</sup> Compatible 5G or LTE FlexModule Mini is required.

<sup>5</sup> Supports 100 peers by default. Expansion to 300 or 500 peers is available via optional software licenses (SFN-LC-300 and SFN-LC-500).

<sup>6</sup> LACP support will be available upon the release of firmware version 8.6.0.

## Ordering Information

---

Product Code	Description
BPL-580X-PRM	Balance 580X

## Featured Add-on

---

Product Code	Description
PRM-J-1Y / PCP-J-1Y	PrimeCare J / PrimeCare+ J (1-Year)
PRM-J-2Y / PCP-J-2Y	PrimeCare J / PrimeCare+ J (2-Year)
PRM-J-4Y / PCP-J-4Y	PrimeCare J / PrimeCare+ J (4-Year)
EXM-MINI-15GN	FlexModule Mini 5G
EXM-MINI-1LTEA-Q	FlexModule Mini LTEA (CAT-12)
EXM-MINI-1LTEA-B	FlexModule Mini LTEA (CAT-6)
EXM-MINI-SIM-8	FlexModule Mini SIM Injector